



Het gebruik van een headset zorgt ervoor dat u handsfree kunt werken. Doordat u nu meerdere dingen tegelijk kunt doen stijgt uw productiviteit.

De Online Indicator geeft aan dat u telefonisch in gesprek bent.

Heeft u meer vragen over de OLI of over headsets, neem dan contact op met uw leverancier. Kijk voor meer informatie over professionele headsets op [www.jabra.nl](http://www.jabra.nl)

## Matrix list (connecting OLI)

Telephone model	TEL	H/SET	Comments
Alcatel	1	1	
Ascom	2	2	
Avaya	2	2	(Call Master 5 and Definity Call Master 5)
Avaya	1	1	
Beocom	2	2	
Cisco (with hs port)	2	2	
Cisco ( <b>without</b> hs port)	1	1	When the telephone is "on hook", the microphone is still active, and OLI may light up if the headset-user is talking continuously.
Ericsson	1	1	
Kirk	2	2	
LG	1	1	
Lucent	1	1	
Matra (with hs port)	1	1	
Matra ( <b>without</b> hs port)	1	1	When the telephone is "on hook", the microphone is still active, and OLI may light up if the headset-user is talking continuously.
Meridian (with hs port)	1	1	
Meridian ( <b>without</b> hs port)	1	1	When the telephone is "on hook", the microphone is still active, and OLI may light up if the headset-user is talking continuously.
Opera	2	2	
Panasonic	1	1	
Philips	1	1	
Samsung	1	1	
Siemens	1	1	
Telenor	1	1	
Telia	1	1	
Tenovis	2	2	

The Matrix list is determined by that the headsets connects to the telephone without using the OLI.

OLI is sensitive the first 5-7 sec. after ending a call, and will easily light up if the headset-user touches the headset.

When the telephone is **on hook**: OLI lights up if the headset-user repeatedly touches the headset.

OLI works for approx 30% of all Telephone switchboards.

If your telephone has not been mentioned in the Matrix list, please begin with code 1+1 and hereafter 2+2.

OLI is designed and developed in Denmark.